Honeywell

VAM VISTA® AUTOMATION MODULE



Honeywell's groundbreaking VISTA Automation Module (VAM) provides VISTA users with easy, affordable home and business control on mobile devices. It's an excellent way to reach new prospects by delivering the lifestyle-enhancing services they demand. With millions of VISTA systems already installed, it's an ideal, economical solution for upgrades and retrofits, and the perfect way to differentiate your business and safeguard your accounts. Choose from black or white models to blend with any décor.

With Honeywell Total Connect[™] Remote Services, users can also view cameras, control their security system, lights, locks and thermostats, and receive event-driven email and video alerts remotely—a great opportunity for additional RMR.

FEATURES

- Centralized local control of the following directly on web-enabled devices:
 - Security
 - Video cameras
 - Z-Wave enabled thermostats, lights, locks, shades
- Built-in web server that broadcasts its own network and allows for local control of the system through any Wi-Fi enabled device (smartphone, iPad[®], iPhone[®], PC, Internet TV, tablet, etc.)
- Built-in Z-Wave controller allows for 232 Z-Wave devices (check compatibility chart for specific devices)
- Connect up to 32 MPEG4, H.264 or OnVIF format IP cameras to a VAM system and view up to four cameras at once (quad view) on local Wi-Fi enabled devices (check compatibility chart for specific devices)
- Supports Honeywell's low-light IP camera (iPCAM-WL) that allows for a better viewing experience in low light and dark areas
- Remote software updates can automatically be sent to any field installed VAM connected to the Internet
 - Ensures that end-users always have the latest VAM features and benefits
- Email notification of system actions and events - Supports up to four different email addresses

- Customize up to 10 scenes to have system devices operate based on time, day or system events
- Sunrise/Sunset Scenes automatically update based on sunrise/sunset times/changes
- Group similar devices (all locks, all cameras, etc.) to reduce programming time and complexity when creating customized scenes
- Compatible with most new and existing VISTA systems (check compatibility chart for specific controls)
- Communicates and gets power over four-wire ECP connection to VISTA
- Choose from black or white models to blend with any décor
- Honeywell Total Connect compatible
- Visit the Tuxedo Touch[™] dealer toolkit at http://www.tuxedotouchtoolkit.com/ for more information about VAM:
 - All compatible Z-Wave devices
 - All compatible IP cameras
 - All compatible tablets/Wi-Fi enabled devices
 - Training videos
 - Sales/introductory videos
 - Product literature and images
 - Latest software revision for manual downloading

VAM VISTA® AUTOMATION MODULE

FEATURES

Compatibility Control Panel

Max. No. of VAM Units

VISTA®-15P/FA148CP	2
VISTA-15PSIA/FA148CPSIA	2
VISTA-20P/FA168CPS	4
VISTA-20PSIA/FA168CPSSIA	4
VISTA-21iP	4
VISTA-21iPSIA	4
VISTA-128BPE/FA1660CE	3
VISTA-128SIAE	3
VISTA-128BPT/FA1660CT	6
VISTA-128BPTSIA	
VISTA-128FBP/FA1670C	3
VISTA-250BPE	3
VISTA-250FBP/FA1700C	3
VISTA-250BPT	6
VISTA-32FBPT	6
VISTA-128FBPT/FA1670CT	6
VISTA-250FBPT/FA1700CT	6



VAM Homescreen on iPad®

SPECIFICATIONS

Physical			
8.25" W x 6.0" H x 0.5" D			
(20.96 cm W x 15.24 cm H x 1.27 cr	n D)		

Wiring(Standard four-wire connection)BlackGroundRed+12VDC (Aux Power)Green"Data in" to control panelYellow"Data out" from control panel

Current Draw 12V, 180mA

ORDERING

VAM	VISTA Automation Module (Black)
VAM-WH	VISTA Automation Module (White)
ZWSTAT	Z-Wave® Thermostat
iPCAM-WL	Wired/Wireless Indoor Low-Light IP Camera (White)
iPCAM-WI2/B	Wired/Wireless IP Camera (White/Black)
iPCAM-WO	Wired/Wireless Outdoor IP Camera (White)

For more information: www.honeywell.com/security

Automation and Control Solutions

Honeywell Security Products Americas 2 Corporate Center Dr. Suite 100 P.O. Box 9040 Melville, NY 11747 1.800.467.5875 www.honeywell.com

L/VAMDLD/D December 2014 © 2014 Honeywell International Inc.

